

## Mechanic

Article nr. 14064R  
 Article name Mechanic  
 Description Durable LED handlamp with 500 and 250 lumens in front. 80 lumens flashlight in top. Charges with USB C

Housing material ABS  
 Lens material PC  
 On/off switch silica gel  
 Battery type 3.7V 2200mAh Li-ion  
 LED type and watt SMD LED/ Main light:6W;Top light:3W  
 Red LED No  
 Colour temperature (Kelvin) 6500K  
 Colour rendering index (CRI) 70+CRI  
 Output (lumens) 500, 250. Flashlight in top 80  
 Run time (hours) Main light 250lm/8h,500lm/4h;Top light:80lm/10h  
 Adjustable beam - zoom in and out No  
 Max charging input 5V 1000mAh  
 Charging time (hours) 3.5h  
 Charging indicator Yes  
 Battery level indicator Yes  
 Charging port USB Type C  
 Cable for charger, 1 m (supplied in box) USB into USB Type C  
 Interchangeable battery No  
 Protection class IP and IK IP 54, IK 07  
 Operating temperature range (Celcius) -10° to +40°  
 Declaration of conformity  
 Packaging FSC cardboard box supplied in FSC cardboard sales display  
 Additional info No plastic inside the box  
 CE (incl ROHS) yes  
 UKCA yes  
 REACH yes  
 MSDS yes

Lamp weight (g) 208g  
 Lamp dimensions (cm) 19.8x5.7x4cm  
 EAN code box (1 pc)  
 EAN code sales display  
 EAN code outer carton  
 Harmonized standard code

Description  
 Box dimensions (cm)  
 Box weight (g)  
 Carton quantity (pcs)  
 Carton size (cm)  
 Carton weight (kg)

### Features



#### The following Safety instructions apply (Where relevant)

##### General Safety instructions

Do not shine in eyes. Do not immerse in water or other liquids. Do not cover the lens when turned on and do not place the product with the lens/light source direct on a surface. Do not operate if the housing, wiring compartment or lens is open, missing, or damaged. Allow the product to cool down sufficiently before cleaning. Do not use cleaners that contain abrasives or solvents. Use on flat, stable surfaces. Do not operate with wet hands. Do not disassemble. Do not attempt to repair if damaged. Repairs must only be carried out by the manufacturer or authorized service representative. Clean with a dry clean cloth. Please note that lighting products generate heat – if the heat exceeds 60 degrees turn off the product.

##### Safety instructions - rechargeable products

Always inspect the charging plug - it must look dry, clean and undamaged. Only use the supplied charging cable and/or charger. Do not use a modified or damaged charger. Do not try to charge the product if it looks damaged. Do not turn on when charging. Do not leave on charge for over 24 hours. Do not charge below 0°C, above 40°C or at high humidity. Do not leave the product on charge near flammable material as it can cause a fire. Never charge without supervision. Always pay extremely attention to Li-ion batteries as they can explode. If not handled properly, the battery may cause explosion, leakage or fire. Do not expose batteries to direct sunlight. Do not disassemble or modify batteries. Do not apply strong impacts to the battery. Do not get batteries wet. Keep batteries out of reach of children and animals. Do not place batteries on top of an electromagnetic field. Do not use batteries that work for an extremely short period of time. Do not short-circuit the battery. Do not put a battery in a microwave oven, pressure container, or other such devices. Do not recharge batteries where heat can build up. If not handled properly, the battery may cause explosion, leakage, or fire.

##### Safety instructions – alkaline batteries

Only use new and undamaged batteries. Remove batteries from a device that is not being used for an extended period as they can leak. Never try to charge a non-rechargeable battery.